

Digital 564



Article

Item no.	Description
101106	Digital 564 4-channel mini hand transmitter, unidirectional, 868 MHz bi.linked

Scope of delivery

- Hand transmitter with battery
- Wall bracket with mounting material

Features

Features

- 4 function keys for free assignment
- Signaling by red LED
- Eyelet for attachment to keychain or lanyard
- High security through 128-bit AES-encrypted radio transmission and constantly changing radio code (rolling code method)

Use

- For all Marantec controls and third-party products (in conjunction with corresponding bi.linked receiver)

Technical data

- Housing type: Mini
- Number of freely programmable keys: 4
- Channels: 4
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: bi.linked
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: RAL 9005 RAL 9016
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 39
- Height [mm]: 92
- Depth [mm]: 12
- Weight [kg]: 0.04
- Packing width: 56
- Packing height: 52
- Packing depth/length: 101
- Packing weight: 0.114
- Freight forwarding articles: No
- GTIN: 4062434000892
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

Accessories

Item no.	Description
167535	Sun visor clip for Mini Hand Transmitters Digital 564, 663, 382, and 384, 10 pieces à
140224	Wall mount mini for mini hand transmitters Digital 564, 663, 382 and 384, 5 pieces

Predecessors

Item no.	Description	Discontinuation
123587	Digital 384 (MFZ)	2023-06-12

Item no.	Description	Discontinuation
160383	Digital 564 4-channel mini hand transmitter, unidirectional, 868 MHz bi.linked, set of 10	2024-01-19
160390	Digital 564 4-channel mini hand transmitter, unidirectional, 868 MHz bi.linked, set of 25	2024-01-19
160397	Digital 564 4-channel mini hand transmitter, unidirectional, 868 MHz bi.linked, set of 50	2024-01-18