Digital 572

Article

Item no.	Description
101115	**Digital 572** 2-channel micro hand transmitter, unidirectional, 868 MHz bi.linked

Scope of delivery

- Hand transmitter with battery

Features

Features

- 2 function keys for free assignment
- Signaling by red LED
- Eyelet for attachment to keychain or lanyard
- High security through 128-bit AES-encrypted radio transmission and constantly changing radio code (rolling code method)

Use

- For all Marantec controls and third-party products (in conjunction with corresponding bi.linked receiver)

Technical data

- Housing type: Micro
- Number of freely programmable keys: 2
- Channels: 2
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: bi.linked
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: RAL 9005 RAL 9016
- Temperature (min.) [°C]: -20
- Temperature (max.) [°C]: 60
- Temperature (min./max.) [°C]: -20/60
- Temperature (min.) [°F]: -4
- Temperature (max.) [°F]: 140
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 39
- Height [mm]: 60
- Depth [mm]: 12
- Weight [kg]: 0.03
- Packing width: 56
- Packing height: 52
- Packing depth/length: 76
- Packing weight: 0.055
- Freight forwarding articles: No
- GTIN: 4062434000922
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

Predecessors

Item no.	Description	Discontinuation
123587	**Digital 384 (MFZ)**	2023-06-12
160382	**Digital 572** 2-channel micro hand transmitter, unidirectional, 868 MHz bi.linked, set of 10	2024-01-19
160389	**Digital 572** 2-channel micro hand transmitter, unidirectional, 868 MHz bi.linked, set of 25	2024-01-19
160396	**Digital 572** 2-channel micro hand transmitter, unidirectional, 868 MHz bi.linked, set of 50	2024-01-19